

Important: Read all instructions prior to installation.


Dual-ended Type B T8/T12 LED Tube

Safety and Notes

- Product should be installed in accordance with all applicable national, state, and local building and electrical codes.
- To reduce the risk of electric shock, ensure that the main power source and circuit breakers are switched off before performing any installation or wiring procedures.
- Avoid looking directly into the lamp when illuminated.
- Designed for direct wire installation only, bypassing existing ballasts where applicable.

Specifications

Specifications	T8B-xKxW-8
Operating Temperature	-4°–140° F (-20°–60° C)
Lens Material	polycarbonate
IP Rating	IP20
Dimmable	No
Connection Type	FA8, dual-end




Modification Label

A label needs to be placed onto the fixture in a location that is visible during retrofit process.

	LED RETROFIT LUMINAIRE CONVERSION BALLAST BYPASS WIRE AS INSTRUCTED IN MANUFACTURER'S INSTRUCTIONS
	Caution—Risk of Injury or Damage: Luminaire has been modified to operate LED lamps. Do not attempt to install or operate fluorescent lamps in this luminaire.

Installation Instructions

1. Remove power from fixture before replacing lamps or modifying ballast.
2. Bypass ballast and use wire nuts to cover any exposed wire ends.
3. Install tubes into fixture.
Note: Make certain tube is rotated so that polycarbonate lens is facing down.
4. Install retrofit label in a visible location on the fixture.



Dual-sided Type B Installation