

Important: Read all instructions prior to installation.

User Manual

SPL-xKxW-60BR

LED Landscape Spotlight

Troubleshooting

Problem	Possible Cause	Probable Solution
Fixture does not light	 There is no power to 12 V power supply. Wire connection loose. Primary landscape wire is not connected to 12 V power supply or wire has a disconnection. Minimum load requirement not met. 	 Check the outlet to 12 V power supply and ensure that a breaker or GFCl circuit has not been tripped. Check wiring to ensure it is securely connected. Check primary landscape wire connection to 12 V power supply. Next, follow wires from fixture to 12 V power supply to ensure continuous run and/or follow wires between problematic fixture and nearest working fixture. Consult power supply specifications/manual and make certain minimum load requirement is met.
Light flickers (one fixture)	 There is a loose connection to primary landscape wire. 	1. Check wire connections.
Light flickers (multiple fixtures)	 There is a loose connection to 12 V power supply. Minimum load requirement not met. 	 Disconnect power to power supply. Check primary landscape wire for loose connections or possible short. Consult power supply specifications/manual and make certain minimum load requirement is met.
Light is dim	 Maximum load of 12 V power supply has been exceeded. Recommended run length of the landscape wire has been exceeded. 	 Check for other lights or load on same system and/or increase 12 V power supply wattage. Increase primary landscape wire gauge size.

* For superbrightleds.com technical help call 866-590-3533 or use our online chat service.

superbrightleds.com

LED Landscape Spotlight

SPL-xKxW-60BR











Important: Read all instructions prior to installation

User Manual

SPL-xKxW-60BR

LED Landscape Spotlight

Safety and Notes

- · For use with outdoor, low-voltage landscape lighting systems only.
- Do not submerge in water—not for use with submersible or pool/spa equipment.
- Light fixture is only compatible with 12-Volt AC or DC power supply. Do not exceed 80% cvof power supply max output.
- Use appropriate landscape wire. (SBL product numbers WP14-2DB or WP12-2DB)

Parts Included

Recommended Accessories

1- Low-Voltage Path Light with Integrated Stake

SBL Part No.	Description
WWN-2212	Silicone Filled Wire nut
SFT-20	Self Fusing Silicone Tape
WP14-2DB	14 Gauge Landscape Wire
WP12-2DB	12 Gauge Landscape Wire

Dimensional Drawings



Installation Instructions

- 1. Lay fixtures out as they will be installed.
- Run landscape wire (WP14-2DB or WP12-2DB available at superbrightleds.com) from 12 V supply past each light. Wire must be within 52" of mounting stake to allow power connections to be made (FIG 1).



- 3. Properly connect each light to landscape wire. Wrap all connections in self-fusing tape (available at superbrightleds.com).
- 4. Using a trowel (and water as needed), loosen ground where fixture will be installed. Gripping the stake ONLY, press stake into ground (FIG 2).

Caution: Do not use a hammer or exert force on fixture itself during installation as doing so may cause damage.

- 5. Turn on 12 V supply and ensure all fixtures are working. If there are any issues, refer to the troubleshooting guide in this manual.
- Dig a small channel—depth of 3" is recommended—and bury landscape wiring and connections. Stone and mulch are also suitable coverings.



