superbrightleds.com

Important: Read all instructions prior to installation.

PAR36 RGB Light with Remote

Safety and Notes

- To reduce risk of electric shock, ensure power is disconnected before performing any installation procedures.
- Avoid looking directly into lamp when illuminated.
- Product should be installed in accordance with local building and electrical codes.

Included Parts

- 1 PAR36 Bulb
- 1 IR Remote Controller

Specifications

PAR36-RGB9W-160-IR	
Operating Voltage	12 VDC/VAC
Rated Power Consumption	9 W
Beam Angle	160°
Dimming	with remote
Operating Temperature	-49–131°F (-45–55° C)
IP Rating	IP68
Remote Type	IR
Remote Battery Type	2032

User Manual

PAR36-RGB9W-160-IR



Remote Diagram



Wireless Remote Functions

ON / OFF

Press 'ON' key to turn on unit or press 'OFF' key to turn off. Retains last setting between power off and power on.

3-Stage Brightness Adjustment

Increases or decreases the brightness of the currently active color. This adjustment doesn't affect patterns.

Color Selection

Activates the static color indicated by the button color.

Patterns

Selecting one of the four patterns will activate that pattern. Patterns operate in RGB mode.

